



ScanSnap S1100



Providing Mac and PC users
the tools to be productive
and paperless...anywhere.





The world's smallest ScanSnap

The ScanSnap S1100 document scanner pushes the limits of size and weight for extreme mobility while delivering smooth full page document scanning. All you need is your laptop and one USB cable to scan and share your documents from just about anywhere, anytime.



Robust plastic card* scanning

In addition to standard and custom size paperwork, the ScanSnap S1100 can scan thick postcards, greeting cards, and even plastic ID cards.

* Up to 0.76 mm thick (card type ISO 7810)



Fast button touch scanning

Quality matters and the ScanSnap S1100 can scan a letter size page in about 7.5 seconds (approximately 8 pages per minute) in color and at a remarkable 300 dpi resolution.*

* The time to scan was measured from the point a page first enters to the point it fully exits the scanner.

Flexible two-way paper path

To best serve the document type being scanned, switch the paper guide to either the “down” position for straight-path feeding or the “up” position for turn-path feeding.

• **Straight-path feeding:** Most suitable for scanning post cards, photos, business cards, plastic cards*, ScanSnap Carrier Sheet, and common office paper.

* This applies to standard ISO 7810 ID-1 card types. Carrier sheets sold separately.

• **Turn-path feeding:** Most suitable for scanning common office paper especially in tight and cluttered environments.

Scanning to the cloud

The ScanSnap S1100 provides users direct scanning to Evernote®* and Google Docs™. Now you can seamlessly scan and save your scanned files to the cloud for fast and easy accessibility from just about anywhere!

* Evernote (Win/Mac) must be installed on the PC/Mac. A Google account (a free service) is required to use Google Docs.

Continuous Document Feeding (CDF)

A tiny ScanSnap doesn't mean miniature performance. The Continuous Document Feeding function allows you to create multiple page PDF files by inserting pages, one after another.

• Scanning a two-sided document using the CDF function



Insert page face-up and press the scan button



The S1100 proceeds to scan the front side.



The page exits facing front side down.



Reinsert the page without pressing the scan button.



The page is scanned. Press the scan button to end the scanning process and create the PDF image file.

Quick Menu application center

After scanning is complete, the selectable Quick Menu appears to allow users to smoothly transition between different scanning intentions without complication or guesswork.



*Scan to PowerPoint® and Rack2-File not available on Mac version.
Evernote (Win/Mac) must be installed on the computer. A Google account (a free service) is required to use Google Docs.*



Intelligent features for nearly effortless scanning

The ScanSnap S1100 features a powerful set of automated image processing functions including Auto skew correction, Auto orientation, and Auto color detection. These intelligent features work behind the scenes to help ensure scanned content looks great without effort.



Efficiently organize data from scanned business cards

Scan your collection of business cards in CardMinder for PC and Cardiris for Mac. Automatically extract the important information and export it into your Outlook, Excel, Address Book (Mac) or other contact management application.



Generate editable Microsoft® Word, Excel, and PowerPoint® files*

Need to make a quick alteration, enhance productivity by scanning paperwork with machine-print back into an editable version with the included ABBYY FineReader for ScanSnap software for PC and Mac.

** Only Microsoft® Word and Excel files can be created for Mac OS. Generated text and images may vary from the original.*



ScanSnap S1100 Case (Sold Separately)*

A convenient carry case is available for S1100.

**This product is not guaranteed to withstand damage by excessive shock or external pressure.*

ScanSnap S1100

Color Image Scanner

General Technical Specifications	
Product Name / Part number	ScanSnap S1100 / PA03610-B005
Scanner Type	Single Sheet, Simplex, Color Scanning with CDF (Continuous Document Feeding)
Scanning Modes	Color, Grayscale, Monochrome, Automatic Mode Detection
Image Sensor	CIS (Contact Image Sensor) X 1
Light Source	3 Color LED (Red, Green, Blue)
Optical Resolution	600 dpi (dots per inch)
Scanning Speed ¹ (A4 portrait / AC Adapter)	Auto Mode ²
	Normal Mode
	Better Mode
	Best Mode
Excellent Mode	7.5 seconds per page
Document Size	Normal Mode
	Normal Mode w/ Carrier Sheet
	Long Document ⁴
Paper Weight (Thickness)	7.5 seconds per page
Paper Setting	Front-side up
Interface ⁵	USB2.0 (USB1.1 Compatible)
Software Interface Driver ³	ScanSnap Manager (TWIN/ISIS™ not supported on Mac or PC) ³
Power Requirement	5V / 0.5A (1 Port)
Power Consumption	During operation: 2.5 W or less, During sleep mode: 1W or less During power off: Less than 0.5 W
Operation Environment	Temperature: 41°F to 95°F (5°C to 35°C) Relative Humidity: 20% to 80% (Non-condensing)
Dimensions (W X D X H) ⁶	10.74 x 1.87 x 1.33 in. (273 x 47.5 x 34 mm)
Device Weight	12.34 ounces (0.77 lbs. or 350 grams)
Environmental Compliance	ENERGY STAR® compliant / RoHS
Limited Warranty	1 year Limited Warranty. For full details, visit www.fcpa.fujitsu.com/warranties or call (800) 626-4686
Service Options	In-warranty Upgrade: Advance Exchange. For full details on all service programs, visit www.ImagingService.com

1: Scanning speeds may vary due to the system environment used. Scanning speed measured from "start feeding document" to "finish output document" after pre-pick and pressing scan button (not including warm-up time). Warm-up time is less than 2 seconds (or less than 3 seconds from chute cover closed). 2: Documents measuring approximately 5.8 inches (148 mm) in length or less are scanned in "Best Mode" while other documents are scanned in "Better Mode". 3: Device cannot be selected as a TWIN, ISIS®, or WIA source. Applications that require these drivers cannot be used directly. 4: S1100 is capable of scanning documents that exceed A4 size in length. This function is available for all modes except excellent mode. 5: PC with USB 3.0 will work as USB 2.0 guaranteed only with USB cable provided with product. 6: When chute is closed.

Software		
Operating System	Windows®	Mac OS
Interface Software ⁷	ScanSnap Manager V5.1 (TWIN / ISIS not supported)	ScanSnap Manager V3.2 (TWIN / ISIS not supported)
Applications	ScanSnap Organizer V4.1	Cardiris™ 4.0 for ScanSnap
	CardMinder™ V4.1	ABBYY FineReader for ScanSnap™ 4.1
	ABBYY FineReader for ScanSnap™ 4.1	Evernote for Mac 3.3
	Evernote for Windows 3.5	
	Scan to Microsoft SharePoint® 4.5	

7: TWIN or ISIS® applications cannot be used directly

Options		
Description	Model Number	Remarks
ScanSnap S1100 Case ⁸	PA03610-0001	Intended for S1100 and included items
ScanSnap Carrier Sheets ⁹	PA03360-0013	Includes 5 individual carrier sheets for use with select ScanSnap products including S1100

8: This product has been especially designed for storing and carrying ScanSnap S1100. Please note that this product is not guaranteed to withstand damage by excessive shock or external pressure. 9: Although ScanSnap Carrier Sheets have a listed lifespan of 500 scans, the lifespan may vary with usage. ScanSnap Carrier Sheets are intended to scan paper documents with weights of 127 g/m² or less. They also support the scanning of folded documents that are as large as 216 x 297 mm.

Consumables		
Description	Part Number	Remarks
Cleaning Wipe	PA03950-0419	1 pack (24sheets) Used to clean rollers



Fujitsu Computer Products of America, Inc.
1250 East Arques Avenue Sunnyvale, CA 94085-4701
(800) 626-4686 • (408) 746-6000
info@fcpa.fujitsu.com • <http://us.fujitsu.com/fcpa>

System Requirements for Windows®					
Compatible Operating Systems		Windows® 8 (32-bit/64-bit)	Windows® 7 (32-bit/64-bit)	Windows® Vista™ (32-bit/64-bit)	Windows® XP (32-bit)
Driver / Application ¹⁰	ScanSnap Manager V5.1	Supported	Supported	Supported ¹²	Supported ¹³
	ScanSnap Organizer V4.1 ¹¹	Supported	Supported	Supported ¹²	Supported ¹³
	CardMinder™ V4.1	Supported	Supported	Supported ¹²	Supported ¹³
	ABBYY FineReader for ScanSnap™ 4.1	Supported	Supported	Supported ¹²	Supported ¹³
	Scan to Microsoft® SharePoint® 3.4	Supported	Supported	Supported ¹²	Supported ¹³
	Evernote for Windows 4.5	Supported	Supported	Supported ¹²	Supported ¹³
Hardware Requirements	CPU ¹⁴	Intel® Pentium® 4 1.8 GHz or higher (recommended: Intel Core 2 Duo 2.2 GHz or higher)			
	Memory Capacity ¹⁴	64-bit: 2 GB or more 32-bit: 1 GB or more		512 MB or More (recommended: 1 GB or more)	
	Display	1,024 x 768 Pixels or more			
	Disk Capacity ¹⁵	2,290 MB free hard drive for installation. 1 GB or more is required for ScanSnap S100 Deluxe. For details, refer to the manual of Rack2-Filer Smart with Magic Desktop			
	DVD-ROM Drive	Required for installation			
	USB Port ^{14, 16}	USB 3.0 / USB 2.0 / USB 1.1			

10: Please refer to the ScanSnap Website for latest support information. 11: The Windows® Desktop search function supports Windows® 7, Windows Vista® and Windows® XP. Search functionality for Windows® XP 200 professional is only supported by Adobe® Acrobat® 7.0 and Adobe Acrobat 8. 12: For use with Service Pack 1 or higher. 13: For use with Service pack 3 or higher. 14: Scanning speed may drop if recommended CPU, memory capacity and USB 1.1 requirements are not met. 15: Microsoft .NET framework 3.5 SP1 will be installed (requires 500 MB of disk space) together with either ScanSnap Manager or ScanSnap Organizer for systems that do not have .NET Framework 3.5 SP1 installed. 16: ScanSnap operates on both USB 2.0 and USB 3.0 without any difference in performance. *System requirements may change depending on the duration of support and the support policy of the companies that make the software listed in the table above.

System Requirements for Mac						
Compatible Operating Systems		Mac OS X v10.8	Mac OS X v10.7	Mac OS X v10.6	Mac OS X v10.5	Mac OS X v10.4
Driver / Application ¹⁷	ScanSnap Manager V3.2	Supported	Supported	Supported ¹⁸	Supported ¹⁹	Supported ²⁰
	Cardiris™ 4.0 For ScanSnap	Supported	Supported	Supported ¹⁸	Supported ¹⁹	Supported ²⁰
	ABBYY FineReader for ScanSnap™ 4.1	Supported	Supported	Supported ¹⁸	Supported ¹⁹	Supported ²⁰
	Evernote for Mac 3.3	Supported	Supported	Supported ¹⁸	Not Supported	Not Supported
Hardware Requirements	CPU ²¹	Intel® Core™ 2 Duo Processor (Recommended: Intel® Core™ 2 Duo 2.4 GHz or higher)		Intel® Core™ 2 Duo 1.83 GHz or higher (Recommended: Intel® Core™ 2 Duo 2.4 GHz or higher)		• Power PC G5 1.6 GHz or higher • Intel® Core™ Duo 1.83 GHz or higher (Recommended: Intel® Core™ 2 Duo 2.4 GHz or higher)
	Memory Capacity ²¹	2 GB or more		1 GB or more		512 MB or more (recommended: 1 GB or more)
	Display	1024 x 768 pixels or more				
	Disk Capacity	1,580 MB free hard disk for installation				
	DVD-ROM Drive	Required for installation				
	USB Port ^{21, 22}	USB 3.0 / USB 2.0 / USB 1.1				

17: Please refer to the ScanSnap Website for latest support information. 18: Mac OS X v10.6.6 or later recommended. 19: Mac OS X v10.5.8 recommended. 20: Mac OS X v10.4.11 recommended. 21: Scanning speed may drop if recommended CPU, memory capacity and USB 1.1 requirements are not met. 22: ScanSnap Operates on both USB 2.0 and USB 3.0 without any difference in performance. *System requirements may change depending on the duration of support and the support policy of the companies that make the software listed in the table above.

Rack2-Filer Smart V1.0 / Magic Desktop V1.0 ^{23, 24, 25} System Requirements (Bundled with ScanSnap S1100 Deluxe only)					
Compatible Operating Systems		Windows® 8 (32-bit/64-bit) ²⁶	Windows® 7 (32-bit/64-bit) ²⁷	Windows Vista® (32-bit & 64-bit) ²⁸	Windows® XP (32-bit) ²⁹
Hardware Requirements	CPU	Intel® Pentium® 4 1.8 GHz or higher (Recommended: Intel® Core™ 2 Duo 2.2 GHz or higher)			
	Memory Capacity	2 GB or more (Recommended: 4 GB or more)			
	Display	1,024 x 768 pixels or higher			
	Disk Capacity	System drive ³⁰	-	64-bit: 2 GB or more	-
	Installation drive	-	32-bit: 850 MB or more	-	
		1GB or more disc space* for each software			
		*Additional space is required for the data created by Rack2-Filer Smart and Magic Desktop			
Supported scanners		ScanSnap iX500, S1500, S1500M, S1300i, S1300, S1100			
Supported mobile devices	Model	iPad series, iPhone series (4 or later), iPod touch series (4th generation or later)			
	OS	iOS 4.3 or later			
	Application	Rack2-Filer Smart for iOS1.1.0 or later			

23: This product only supports Microsoft® Windows®. 24: Please refer to the Rack2-Filer Smart Web site and the Magic Desktop Web site. 25: When installing Magic Desktop, Internet connection is required. 26: Rack2-Filer Smart and Magic Desktop runs as a desktop application. 27: For use with Service pack 1 or higher. 28: For use with Service pack 2 or higher. 29: For use with Service pack 3 or higher. 30: This is the free capacity required when .NET Framework 4 is not installed.

Included items	
• Getting Started • Setup DVD-ROM • USB Cable (2.0 m) • Rack2-Filer (provided with ScanSnap S1100 Deluxe Bundle)	

