

ScanSnap sveod

A New Perspective on Scanning







Scansnap





shaping tomorrow with you





Redefining what a document scanner can do!

ScanSnap

Overhead scanning made simple

Scan newspapers, magazines or books directly without cutting or damaging them.

Preserve delicate documents or books

Some things can't be scanned through a feeder so ScanSnap SV600 operates by taking an elevated view altogether.

Scan business cards to large A3 size (double-letter) documents

ScanSnap SV600 breaks free from typical flatbed limitations by scanning content larger than just letter size. Simply position the document on the A3 scan mat and press scan.

17

Save time, save effort

Make it an easy job by scanning not only books or magazines but all types of content restrained in binders, spirals, folders, or clear sleeves... just flip the page and scan.

FUĴITSU



VI Technologies (Versatile Imaging)

Combining high quality CCD optics and advanced LED illumination, ScanSnap SV600 uses advanced capture technologies to maximize field of depth and minimize unevenness page after page.






Smooth operation in overhead scanning

ScanSnap SV600 is enhanced with new customized features while continuing the ScanSnap concept: Simple, Fast and Compact.

Quick Menu saves time!

service like Evernote or Dropbox.


The Quick Menu pops up after scanning to allow users a fast and productive way to store, share or transform their scanned data either on the computer or into a favorite cloud



Automatically crop several documents at once with "Multiple Document Detection"

With an advanced cropping and orientation technology built-in, ScanSnap SV600 can scan several business cards, photos, newspaper clippings and other documents at one time.





Performance matters.

With the touch of the power button, ScanSnap SV600 is ready to scan in just 3 seconds! And with each press of the scan button, a large A3 dimension scan area is captured in less than 3 seconds. Combined with intelligent image correction, great results are just a button push away.











Easily create your own digital books

ScanSnap SV600 is your ultimate partner to scan books or magazines efficiently. With "Rack2-Filer Smart with Magic Desktop" software (PC only), you can scan, organize and create your own digital books.

Step 1: Scan with one button!

Place the book on the mat and press the scan button.

Page Turning Detection – SV600 detects when a page is turned and automatically begins scanning.

Timed Mode – Set a fixed time interval and SV600 scans in real time with you.

Step 2: Auto image correction

Auto Image Correction – Automatically crops, de-skews and sets the orientation of multiple sheets placed on the mat.

Auto Book Correction - Automatically flattens and corrects the curve distortion of books and magazines.



Book image correctionFlattens and corrects curve distortion.



Point retouch functionFingers captured during scanning can be removed.

Step 3: Organizing and Viewing

With the included ScanSnap Organizer, CardMinder and Rack2-Filer Smart software (PC only), keeping scanned content organized and accessible is a Snap!

Rack2-Filer Smart with Magic Desktop (PC only)
























ScanSnap SV600 Technical Specifications

■ General Specifications

Description		ScanSnap SV600 / PA03641-B005	
Scanner type		Over Head system, simplex scanning	
Scanning modes		Color, grayscale, monochrome, Automatic (color, grayscale, monochrome detection)	
Image senso	r	Lens reduction optics / color CCD x 1	
Light source		(White LED + lens illumination) x 2	
Optical resolu	ution	Horizontal scanning: 285 to 218 dpi, Vertical scanning: 283 to 152 dpi *1	
	Auto mode *3	"Better mode" or "Best mode": 3 seconds / page	
	Normal mode	Color / Grayscale: 150 dpi, Monochrome: 300 dpi 3 seconds / page *4	
Scanning speed	Better mode	Color / Grayscale: 200 dpi, Monochrome: 400 c 3 seconds / page *4	
(A3 landscape)	Best mode	Color / Grayscale: 300 dpi, Monochrome: 600 dp 3 seconds / page *4	
	Excellent mode	Color / Grayscale: 600 dpi, Monochrome: 1,200 dpi 3 seconds / page *4	
Document size		Automatically recognizes document size, A3(landscape), A4(landscape), A5(landscape), A6(landscape), B4(landscape), B6(landscape), B6(landscape), Post card, Business card, Double Letter(landscape), Letter, Legal(landscape) and Custom sizes (Max: 432 x 300 mm (17.0 x 11.8 in.), Min: 25.4 x 25.4 mm (1 x 1 in.)) **S	
Document th	ickness	30 mm (1.18 in.) or less	
How to start scanning *6		Select one of the below. 1. Normal scan: Press "Scan" button for every page 2. Timed Interval Scanning (Timed Mode) 3. Page turning detection	
Interface *7		USB2.0 / USB1.1 (connector: B Type)	
Image processing functions		Deskew by text on document, Auto paper size detection, Auto image rotation, Auto color detection, Book image correction *8, Multiple document detection *9	
Magnification in vertical scanning (length)		±1.5%	
Power requirement		AC 100 to 240 V, 50 / 60 Hz	
Power consumption		During operation: 20 W or less During sleep mode: 2.6 W or less During standby: 0.4 W or less	
Operation environment		Temperature: 5 to 35 °C (41 to 95 °F) Relative humidity: 20 to 80 % (Non-condensing)	
Dimensions (WxDxH)		210 x 156 x 383 mm	
Device weight		3 kg (6.613 lb)	
Environmental compliance		ENERGY STAR® / RoHS / EPEAT Silver	
Driver		Specific driver (Does not support TWAIN / ISIS®)	

- *1 Optical resolution differs due to different scanning angle on the same document.
- Scanning speed may vary due to the system environment used.

 Switch between "Better mode" and "Best mode" depends on the length of the document. A4 (portrait):
- 200 dpi. A6 size or below: 300 dpi
- *41 Time between actual start of scanning (scanning pad) and finish scanning.

 *5 For documents of thickness over 6 mm, the maximum document size is 400×300 mm.

 *6 When performing continuous scanning, time is needed for the scanning head to return to its original position.
- *7 Compatible with USB3 0 port but connection will run as USB2 0 speed
- *8 Automatically correct distortion caused by the curve of an opened book or magazine. *9 Digitize multiple documents by automatically cropping several documents in one scan.

■ Software

		Windows®	Mac OS		
Driver *1 *2		ScanSnap Manager V6.2	ScanSnap Manager V6.2		
		ScanSnap Organizer V5.1	ScanSnap Organizer V1.0		
		CardMinder V5.1	CardMinder V5.1		
		ABBYY FineReader for ScanSnap™ 5.0	ABBYY FineReader for ScanSnap™ 5.0		
	Applications	•	ABBYY FineReader Express Edition for Mac 8.3		
		Scan to Microsoft® SharePoint® 3.4	=		
		Adobe® Acrobat® Standard	=		
	Evernote for Win 4.5		Evernote for Mac 3.3		

- *1 TWAIN or ISIS® applications cannot be used directly.
 *2 "One Touch" image file (JPEG, PDF and searchable PDF) generation.
- These functions are operable with ScanSnap Manager (ScanSnap specific driver)

■ ScanSnap SV600 System Requirements

Windows®

· · · · · · · · · · · · · · · · · · ·					
Compatible operating systems		Windows® 8 (32-bit / 64-bit) *1	Windows® 7 (32-bit / 64-bit) SP1 or later	Windows Vista® (32-bit / 64-bit) SP2 or later	Windows® XP (32-bit) SP3 or later
	ScanSnap Manager V6.2	Supported	Supported	Supported	Supported
	ScanSnap Organizer V5.1	Supported	Supported	Supported	Supported
	CardMinder™ V5.1	Supported	Supported	Supported	Supported
Driver / Applications	ABBYY FineReader for ScanSnap™ 5.0	Supported	Supported	Supported	Supported
*2	Scan to Microsoft® SharePoint® 3.4 *3	Supported	Supported	Supported	Supported
	Adobe® Acrobat® Standard *4	Please refer to the Web site of Adobe Systems Incorporated for latest support information.			
	Evernote for Win 4.5	Supported	Supported	Supported	Supported
	CPU	Intel® Core™ i5 2.5 GHz or higher			
	Memory capacity	64-bit: 4 GB or more 32-bit: 4 GB or more			
Hardware requirements *5	Display	1,024 x 768 pixels or more 800 x 600 pixels or higher			nigher
	Disk capacity *6	4,350 MB free hard disc space for installation			
	DVD-ROM drive	Required for installation *7			
	USB port *8	USB 3.0 / USB 2.0 / USB 1.1			
*1 Function as a deskton application					

- *1 Function as a desktop application
- *2 Operating systems listed in this table are the only ones supported. Please refer to the ScanSnap Web site for latest support information.
- *3 The software is available to be downloaded from ScanSnap website *4 Requires Internet Explorer 7.0 or later; or, Firefox 3.5 or later.
- **4 Requires internet explorer 7.0 or later; or, Friency 3.5 or later; does not meet these requirements.
 *5 The ScanSnap device may not work if the connected computer does not meet these requirements.
 *6.NET Framework 3.5 SP1 will be installed (requires 500 MB of disk space) together with either ScanSnap Manager, ScanSnap Organizer or CardMinder for systems that do not have NET Framework 3.5 SP1 installed.
 *7 Please refer to the web site if you do not have a DVD-ROM drive. http://scansnap.fujitsu.com/g-support/en/ *8 Compatible with USB3.0 port but connection will run as USB2.0 speed. Scanning speeds may drop if USB
- 1.1 requirements are not met. * System requirements may change depending on the duration of support and the support policy of the companies that make the software listed in the table above.

• Mac OS

Comp	Compatible operating systems		OS X v10.9	Mac OS X v10.8 (Recommended: 10.8.5 or later)	Mac OS X v10.7 (Recommended: 10.7.5 or later)
	Driver / Applications + 1 *2	ScanSnap Manager V6.2	Supported	Supported	Supported
		ScanSnap Organizer V1.0	Supported	Supported	Supported
		CardMinder V5.1	Supported	Supported	Supported
		ABBYY FineReader for ScanSnap™ 5.0	Supported	Supported	Supported
		ABBYY FineReader Express Edition for Mac 8.3	Supported	Supported	Supported
		Evernote for Mac 3.3	Supported	Supported	Supported
	Hardware requirements	CPU	Intel® Core™ i5 2.5 GHz or higher		
Handun		Memory capacity	4 GB or more		
		Display	1,024 x 768 pixels or higher		
*3		Disk capacity	2,480MB free hard disc space for installation		
		USB port *4	USB3.0 / USB2.0 / USB1.1		
USB port *4		0000.07 0002.07 0001.1			

- *1 This product supports Mac operating systems.
- *2 Operating systems listed in this table are the only ones supported. Please refer to the ScanSnap Web site for latest support information. If a Setup DVD-Rom in the product box does not contain the driver and applications for Mac OS, please visit the following web page: http://scansnap.fujitsu.com/g-support/en.
- *3 The ScanSnap device may not work if the connected computer does not meet these requirements.

 *4 Compatible with USB3.0 port but connection will run as USB2.0 speed. Scanning speeds may drop if USB
- * System requirements may change depending on the duration of support and the support policy of the companies that make the software listed in the table above.

■ Rack2-Filer Smart V1.0 / Magic Desktop V1.0 *1*2 System Requirements

Windows® 8 Windows® 7 Windows Vista® Windows Vista® Windows Vista® Windows Vista® (32-bit / 64-bit) (32-bit / 64-bit) (32-bit / 64-bit) (32-bit / 64-bit)	vs® XP		
	bit) r later		
Intel® Pentium® 4 1.8 GHz or higher (Recommended: Intel® Core™ 2 Duo 2.2 GHz or l	Intel® Pentium® 4 1.8 GHz or higher (Recommended: Intel® Core™ 2 Duo 2.2 GHz or higher)		
Memory capacity 2 GB or more (Recommended: 4 GB or mor	2 GB or more (Recommended: 4 GB or more)		
Display 1,024 x 768 pixels or higher			
Hardware requirements System 64-bit: 2 GB or more			
Disk drive *4 - *5 32-bit: 850 MB or more			
capacity Installation drive 1 GB or more disc space for each software * Additional space is required for the data created by Rack2-File and Magic Desktop	d for the data created by Rack2-Filer Smart		
Supported scanners ScanSnap SV600, iX500, S1500, S1300i, S1300,	ScanSnap SV600, iX500, S1500, S1300i, S1300, S1100		
Model iPad series, iPhone series (4 or later), iPod touch series (4th generation or later)	iPad series, iPhone series (4 or later), iPod touch series (4th generation or later)		
iOS OS iOS 4.3 or later			
Supported Applications Rack2-Filer Smart for iOS 1.1.0 or later			
mobile Model ARM compatible processor	ARM compatible processor		
devices OS Android OS 2.2 or later	Android OS 2.2 or later		
Android Memory capacity 512 MB or more			
Applications Rack2-Filer Smart for Android 1.1.1 or later			

- *1 Operating systems listed in this table are the only ones supported. Please refer to the Rack2-Filer Smart Web site
- Poperating systems issted in this table are the only ories supported. Please and the Magic Desktop. Web site for latest support information.
 When installing Magic Desktop, Internet connection is required.
 Rack2-Filer Smart and Magic Desktop run as a desktop application.
 This is the free capacity required when .NET Framework 4 is not installed.

- *5 Disk capacity is not necessary as Microsoft® .NET Framework 4.5 is included in Windows® 8.

■ Included items

Description

Background Pad

- AC cable Background Pad Rack2-Filer Smart with AC adapter Set-up DVD-ROM Magic Desktop DVD-ROM
- USB cable ■ Option

Part number

PA03641-0052

Adobe® Acrobat® DVD-ROM Extenders (x2)

*One pad is bundled with the scanner

Remarks Set in front of the scanner when scanning.

■ Cleaning Materials

Description	Part number	Remarks
F1 Cleaner	PA03950-0352	100 ml bottle For cleaning the glass, camera, lamp etc of the scanning head.
Cleaning Wipe PA03950-0419 1 pack (24 sh Wet tissue wi For cleaning th		1 pack (24 sheets) Wet tissue with "cleaner F1". For cleaning the glass, camera, lamp etc of the scanning head.



This product is a green product and Fujitsu promotes recycling for the scanner, PFU LIMITED, a Fujitsu company, has determined that this product meets the Energy Star® guidelines for energy efficiency. ENERGY STAR® is a registered trademark of the United States.



This scanner is designed to digitize materials that can be reproduced lawfully, in accordance with applicable copyright regulations and other laws. ScanSnap users are solely responsible for how they use this scanner. It is

imperative that ScanSnap users comply with all applicable local rules and laws, including, without limitation, copyright laws when using this scanner.

©2013 Fujitsu Computer Products of America, Inc. All rights reserved. Fujitsu and the Fujitsu logo are registered trademarks of Fujitsu Limited. ABBYY™ FineReader™ Engine ©2011 ABBYY. OCR by ABBYY, ABBYY and FineReader are trademarks of ABBYY. Adobe, Acrobat are either registered trademarks or tradenames of Adobe Systems Incorporated in the United States and/or other countries. Evernote is a registered trademark or trademark of Evernote Corporation, Google, Google Docs, Android and Google Play are registered trademarks or trademarks of Google Inc. Intel. Pentium, and Intel Core are registered trademarks or trademarks of Intel Corporation in the United States and other countries, ISIS® is a registered trademark of EMC Corporation in the United States, Mac, Mac OS, OS X, IPad, IPhone and App Store are trademarks of Apple Inc. Microsoft, Windows, Windows Vista, Excel, PowerPoint, SharePoint and Internet Explorer are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries. Word is the product of Microsoft Corporation in the United States, ScanSnap, ScanSnap, Iogo, ScanSnap Manager, ScanSnap Organizer, CardMinder and Rack2-Filer are registered trademarks or trademarks of PFU LIMITED in Japan, Wi-Fi and Wi-Fi Protected Setup are trademarks of Wi-Fi Alliance, Other company names and product names are the registered trademarks or trademarks of the respective companies. Specifications are subject to change without notice. All statements herein are valid in the US for US residents only, are based on normal operating conditions, are for informational purposes only, and are not intended to create any implied warranty of merchantability or fitness for a particular purpose. DS399000915

